

17.4 Conversion table for three-phase autotransformers

Type power KVA	Throughput power					
	230:115	400:230	415:380	440:380	500:200	500:380
0.10	0.20	0.24	1.20	0.74	0.18	0.42
0.13	0.26	0.30	1.50	0.96	0.23	0.54
0.16	0.32	0.38	1.90	1.20	0.28	0.67
0.20	0.40	0.47	2.40	1.50	0.36	0.84
0.25	0.50	0.60	3.00	1.80	0.45	1.00
0.32	0.64	0.76	3.80	2.30	0.57	1.30
0.40	0.80	0.95	4.80	2.90	0.72	1.70
0.50	1.00	1.20	6.00	3.70	0.90	2.10
0.63	1.26	1.50	7.50	4.60	1.10	2.60
0.80	1.60	1.90	9.50	5.90	1.40	3.30
1.00	2.00	2.40	11.90	7.40	1.80	4.20
1.50	3.00	3.50	17.90	11.10	2.70	6.30
2.00	4.00	4.70	23.80	14.80	3.60	8.40
2.50	5.00	6.00	29.70	18.50	4.50	10.50
3.00	6.00	7.10	35.70	22.50	5.40	12.60
3.50	7.00	8.30	41.60	26.00	6.30	14.70
4.00	8.00	9.50	47.60	29.00	7.20	16.80
4.50	9.00	10.70	53.50	33.00	8.10	18.90
5.00	10.00	12.00	59.50	37.00	9.00	21.00
6.00	12.00	14.30	71.40	44.00	10.80	25.20
7.50	15.00	17.84	89.25	55.00	13.50	31.50
8.80	17.60	21.00	104.00	65.00	15.80	37.00
10.00	20.00	23.80	119.00	74.00	18.00	42.00
12.50	25.00	30.00	148.00	92.00	22.50	52.00
15.00	30.00	35.70	178.00	111.00	27.00	63.00
17.50	35.00	41.60	208.00	129.00	31.50	73.00
20.00	40.00	47.60	238.00	148.00	36.00	84.00
22.50	45.00	53.00	267.00	166.00	40.00	94.00
25.00	50.00	59.50	297.00	185.00	45.00	105.00
30.00	60.00	71.00	357.00	222.00	54.00	126.00
35.00	70.00	83.00	416.00	259.00	63.00	147.00
40.00	80.00	95.00	476.00	296.00	72.00	168.00