

## Mission 1000-3000 VA



### Wall mounting or installation in the control cabinet

- ❖ Capacities from 1000 VA to 3000 VA
- ❖ RS232 interface
- ❖ CE certification
- ❖ EMC standard IEC62040-2, IEC61000-4-2 to -5
- ❖ Service-friendly design
- ❖ SNMP optionally available

## Technical specifications

Input	single phase 115 + -5VAC - 295 + -5VAC
Frequency range	45- 55Hz or 55-65Hz
Power factor	> = 0.98
Bypass area	186VAC- 252VAC
Output	single phase 208/220/230 / 240VAC + -2%
Power Factor	0.8
Rated frequency output	50/60 + -0,2Hz
Performance of	network operation > = 87%
	Battery operation > = 85%
	ECO > = 94%
	each with a charged battery
Distortion	<= 3% at linear load
Output voltage	<= 5% with non-linear load
Battery voltage	24 or 48 or 72VDC
Battery type	standard 12V / 7Ah maintenance-free
Charging current	1A
Ambient temperature	0-40 ° C
Relative humidity	0-95% non-condensing
Altitude	<1500m
Storage temperature	-25 to 55 ° C

### Contact details

Trafo Schneider GmbH  
Waidmattenstr. 8  
D- 79232 March-Buchheim

phone            0049 (0) 7665 92 30 0  
fax                0049 (0) 7665 92 30 22  
e-mail            info@trafo-schneider.de  
internet          www.trafo-schneider.de

sales tax identification number corresponding to § 27 a value added tax act: DE13593847

#### Approach

A5 exit Freiburg Mitte coming from Basel – turn into direction Umkirch - after 1.7 km turn to the right into direction March on L 116 – cross railway and keep straight on for 500 m. At the second traffic lights turn to the left into direction Gottenheim - Follow L 187 ca. 400 m than turn to the right into Am Untergrün - After ca. 100 m you reached the target.

A5 exit Freiburg Nord coming from Karlsruhe – turn to the right into direction Holzhausen follow Benzhauserstraße for 1.2. km – At the next crossroads turn to the left into Buchheimerstraße and follow it 1.6 km - In Buchheim turn to the left follow Hauptstraße 500 m and turn to the right at the second traffic lights into Stegenbachstraße – Follow 400 m than turn to the left into Am Untergrün - After ca. 100 m you reached the target.